



## AUTOCOPY ROLLING CODE 301H-5HS

No any machine is required to duplicate it. It duplicates code and frequency in the same step. It makes the duplication of any code in at least 3 seconds. Frequency range: from 250 MHz till 450 MHz's one fixed frequency in 433.92 SAW and 3 different ones. This door opener is compatible with the 95% of the models in the market. It is elegant, light and with big buttons for your comfort. Weight: 31.5 gr. Size: long 62.8mm width 33.5mm thickness 13.8mm It allows to stock till 4 different frequencies. It is registered and fulfills the European normative.

### Programming:

1. To put the door opener in the programming mode, press the button 1 and 2, keep pressing till the LED light on and off 3 times if you want to program a 433.92 door opener or, twice if you want to duplicate other door opener with frequency different than 433.92.
2. Press any button on the 301H5HS, the LED will light on and off very quickly, do not release.
3. Press the button on the original door opener you want to duplicate; place one in front of each other (see picture below), transmit towards left side of the 301H5HS beginning at a distance of 15 cm and getting closer till the LED in the 301H5HS light on and after few seconds it will light off (it will beep once, then it will light on and after few seconds will light off indicating it is memorized). Do the same steps again for the other buttons if necessary, but, do not forget which frequency we want to memorize on the programmable door opener, as indicated on paragraph one.

