



AUTOCOPY ROLLING CODE 301H-5HE

Auto copy rolling code door opener for the following brands: JCM, PUJOL, FORSA, DMIL, MASTER INGENIEROS, NUEVA CASTILLA, ELEMAT, ZIBOR, HYDOM, EMFA, CUBELLS, ALFA TORRES, ELECTRO PARKING, EP, NEO, ARF-2. It is also valid when the original one has an installer code. No duplicating machine is required to program this duplicate auto copy door opener.

PROGRAMMING

For duplication follow next steps:

1. Insert the jumper in the metallic terminal to activate the programming directions.
2. Press and keep pressing the button 1 in the door opener 301H-5HE. The light on the door opener will flicker quickly once and then it will turn off.
3. While keeping the button 1 pressed, press at the same time one of the buttons on the original door opener; very close to the receiving area (upward on the right). The light on the 301H-5HE will light on once slowly and then it will light off.
4. Follow steps 2 and 3 again but this time press button 2 on the 301H-5HE instead button 1. The light on the 301H-5HE will flicker the same as previous steps.
5. Press button 3 or 4 and then releases it. The light on the 301H-5HE will flicker quickly and after 10 seconds it will stay fixed, it means that programming has been successful. If the light flickers three times slowly and lights off, please repeat the same steps from the scratch. In case it happens again this original door opener could not be duplicated with an auto copy transmitter.
6. to place the 301H-5HE in programming direction. Do not stock this model door openers with the jumper inserted in both metallic terminals in order to avoid that the battery runs down.
7. Do not forget that register the new door opener in the receiver is required.